

### **Further information / Accessory**

Accessory: Data-key DK pro and Programming package PP 50 pro / PP 60 pro (not included in delivery of the time switch)



Accessory: Radio receiver DCF-Time FU 20.00 pro (not included in delivery of the time switch)

Accessory: Radio receiver GPS-Time FU 3x.00 pro (not included in delivery of the time switch)



Accessory: Mini terminal box 4PLE – 70 mm, for wall mounting (not included in delivery of the time switch)

# Overview time switch function (Functions similar to SC 88.10 pro)

- 1 channel (change-over)
- Daily and weekly program
- 300 memory locations
- Minimum interval 1 min.
- Permanent by date
- Manual override
- Elapsed time and pulse counter
- Pulse function
- Cycle function
- Timer function
- Channel button function
- DCF function
- Data-key function

# Save time

# SC 58.17 pro

#### Masterclock

- For approx. 20 slave clocks (24 VDC, 150 mA, pole changing pulse)
- Short-circuit proof
- Automatic adjustment of the slave clocks
- Automatic time correction of slave clock/s after supply voltage interruption
- Repetition of the last applied minutepulse
- 10 years battery-reserve
- Fully automatic summertime change (European standard) with 60 additional pulses or pulse suppression for 1 hour of the slave-clock-line
- Monitoring of the slave-clock-line and malfunction indicator in display
- Security by PIN-Code
- Illuminated display
- Data-key function
- DCF function

### **Highlights**

- Text based menu and self-explanatory symbols
- Display with a large dot matrix area to provide two high resolution text lines
- Easy handling. Quick and intuitive programmable time switch
- Can be programmed with supply disconnected
- Unlimited program security by E²-PROM
- Programmable with PC
   (Accessory Data-key DK pro and Programming package PP 50 pro / PP 60 pro)

# Digital time switches as masterclocks SC 58.17 pro

for DIN-rail mounting

## Technical data masterclock unit

24 VDC		
150 mA		
approx. 20 slave clocks à 7 mA		
Pole changing pulse		
Normal operation 1/min.; during adjustment 10/min.		
approx. 2 sec. (adjustable)		

# Technical data / Technical data time switch unit

Supply voltage	230 V, 50-60 Hz		
Power consumption (real power)	1.7–2.9 W (depending on the switching status)		
Channels (potential-free)	Change-over, contact gap $<$ 3 mm ( $\mu$ )		
Contact material	AgNi		
Switching capacity per channel	10 A / 250 V~ at cosφ=1		
88* ** 1 *	6 A with inductive load cosφ=0.6		
Min. switching power	300 mW (5 V / 5 mA)		
Max. starting current	30 A		
Filament Lamp, Halogen Lamp	400 W		
Fluorescent Lamp with electron. lamp ballast	100 W		
Fluorescent Lamp with convent. lamp ballast	100 W		
LED (230 V~) / CFL	50 W		
Switching functions	ON; OFF; pulse; cycle		
Pulse length	00:01 up to 59:59 mm:ss		
Pulse length Timer (man. switching)	0:00:01 up to 9:59:59 h:mm:ss		
Pulse/Pause length Cycle	0:00:01 up to 9:59:59 h:mm:ss		
Memory locations	300		
Minimum interval	1 min.		
Time base	Quartz or DCF / GPS (FU 20.00 pro / FU 3x.00 pro)		
Quartz accuracy (at 20°C)	$\leqq \pm 0.5~\text{sec./day}$ (Quartz accuracy optimized for typical ambient conditions)		
Power back-up (at 20°C)	approx. 10 years (depends on the Lithium-battery life)		
Program security	unlimited (E <sup>2</sup> -PROM)		
Display	high resolution LCD (visible area 12.8 cm²)		
Permitted ambient temperature	−30°+50°C		
Housing	self-extinguishing thermoplastic		
Dimensions	45 x 71.5 x 58 mm		
Mounting	35 mm DIN-rail		
Type of connection	Screw terminals (Pull-up type)		
Type of protection	IP 20 to DIN EN 60529		
Class of protection	II when installed according to regulations		
Mode of operation (DIN EN 60730-1)	1 BSTU		
Degree of contamination (DIN EN 60730-1)	2		
Rated surge voltage (DIN EN 60730-1)	4 kV		
Accessories (not included in delivery)	Data-key DK pro, Radio receiver FU 20.00 pro / FU 3x.00 pro, Programming package PP 50 pro / PP 60 pro, Mini terminal box 4PLE		

Order number	Number of slave-clock-lines	Channels	Time base
SC 58.17 pro	1	1	Quartz/DCF
Housing colour			





