

MI.PUCK SYSTEM

müller EA 66.11 pro4 mi.puck astro dimmer



Overview

- Astro dimmer (remote-controllable)
- Dimmer for dimmable LED lamps / trailing edge dimming
- Minimum and maximum dimming-value adjustable
- Adjustable switch-on dimming-value or memory function
- Staircase lighting function
- Battery backup
- Integrated Bluetooth
- mi.system mesh
- Programmable and controllable via app (iOS and Android)
- Switching program can be deactivated via app
- Compact insert housing for flush-mounting
- Protection against overload, overvoltage, short circuit and overheating

MI.PUCK SYSTEM




müller EA 66.11 pro4 mi.puck astro dimmer

Order information

	EAN	Art. No.
EA 66.11 pro4	4022709242068	24206

Technical data

Supply voltage	230 V, 50 Hz
Power consumption (real power)	0,3 W
LED (230 V~)	ε 4-150 W
Transmission type	Bluetooth LE Range max. 75 m
Switching functions	Astro - ON/OFF Night - ON/OFF Extra - ON/OFF Permanent - ON/OFF
Offset Astro switching time	+/-90min.
Memory locations	100
Time base	Quarz
Quartz accuracy	≤±0,5 Sek./day (Quartz accuracy optimized for typical ambient conditions)
Power back-up (at 20 °C)	approx. 10 years
Program security	unlimited
Permitted ambient temperature	-25...+45 °C
Housing	self-extinguishing thermoplastic
Mounting	Flush-mounting
Type of connection	Screw terminals
Type of protection	IP 20 to DIN EN 60529
Class of protection	II when installed according to regulations
Minimum requirement	Android version 7.0 iOS version 12.0 Bluetooth 4.0
Accessories (free download)	Programmable and controllable with smartphone via Bluetooth: App - mi.puck



Rights to technical amendments reserved / Technische Änderungen vorbehalten
Droits de modifications techniques réservés / Suscettibile di errori e modifiche